

Lux Meter

LX104



Features :

- 3¾ Digital Multimeter
- 4000 Counts with Bar graph 61 Segments
- Auto Ranging
- Peak Hold
- Max. & Data Hold
- Auto Power Off
- Low Battery indication
- User selectable FC / Lux
- **USB Computer Interface**
(Advanced Software Program for all windows)
- **Capacity of Data Logging 99**



Technical Data :

Basic Function	Range
Measure Range	400,000Lux
Accuracy	$\pm 5\% \pm 10d$ (<10,000 Lux)
	$\pm 10\% \pm 10d$ (>10,000 Lux)
Max. Resolution	0.1 Lux / 0.01 Fc
Measuring Rate	1.5 times/second

- **Standard Accessories** : Soft carrying case, Gift Box, Manual
Photo Detector and USB Cable, CD Software.
- **Dimension** : Photo Detector : 115(H) x 60(W) x 27(D)mm
Meter Body : 203(H) x 75(W) x 50(D)mm